Send NV images to SRP350

- 1. Download Samsung NV Bit Map Logo Utility from <u>www.goodson.com.au/support</u>
- 2. UN-Zip the file to a fold (eg. C:\SamNV37)
- 3. Make sure the logo image is saved as "Monochrome Bitmap" format, and maximum horizontal image size is 512 pixels.
- Start \rightarrow Run \rightarrow "C:\SamNV37\NV Image Tool ver 3.7.exe" (screen should similar this) 4. ₩NY Download Utility 3.7 No. Name Bitmap Selection Change Color Range Color-Logo Files : 0 / 256 Logo Size Total : 0 / 256 KByte C Red Open File THRESHOLD 0 Port Configuration-R Color(Cartridge) C Greet SRP-350 • Remove ┢ C Blue Direct Port C Windows Driver Reset L Color(Cartridge) Not Used 100 -R Value Direct Port Configuration-Color Change Select (Invert to L Cartridge Download. Port Setting Port : LPT1 100 Save File. L Value EXIT Print
- 5. From Port Configuration, Select Printer Model

No.	Name	Size			
no Files : O					
go nics . o	/ 256	Bitmap Selection	Change Color Range	Color	
go Size To	/ 256 tal : 0 / 256 KByte	Bitmap Selection Open File	Change Color Range	Color	C Red
go Files : o go Size To Port Configu	/ 256 tal : 0 / 256 KByte aration	Bitmap Selection	Change Color Range	Color R Color(Cartridge)	C Red C Green
ort Configu	/ 256 tal : 0 / 256 KByte aration	Bitmap Selection Open File Remove	Change Color Range	R Color(Cartridge)	C Red C Green
ort Configu ort Configu OFP-350 OFP-103 OFP-131	/ 256 tal : 0 / 256 KByte iration	Bitmap Selection Open File Remove Reset	Change Color Range	R Color(Cartridge)	C Red C Green C Blue
go Size To Port Configu SRP-350 STP-103 STP-131 SRP-350	/ 256 ral : 0 / 256 KByte iration	Bitmap Selection Open File Remove Reset	Change Color Range THRESHOLD 0	Color R Color(Cartridge) L Color(Cartridge)	C Red C Green C Blue C Not User
ort Configues ort Configues STP-103 STP-131 STP-350 SRP-370 SRP-370 SRP-372	/ 256 ral : 0 / 256 KByte rration	Bitmap Selection Open File Remove Reset	Change Color Range	Color R Color(Cartridge) L Color(Cartridge)	C Red C Green C Blue O Not User
201 Size To 201 Configu 201 C	/ 256 ral : 0 / 256 KByte rration	Bitmap Selection Open File Remove Reset Download.	Change Color Range	Color R Color(Cartridge) L Color(Cartridge) Color(Cartridge)	C Red C Green C Blue C Not Use nge Select L Cartridge)
o Size To ort Configu Cont Configu Control (Configu- Control (Configu- Configu	/ 256 ration	Bitmap Selection Open File Remove Reset Download. Save File	Change Color Range	Color R Color(Cattridge) L Color(Cattridge)	C Red C Green C Blue C Not Use nge Select L Cartridge)
o Size To ort Configu STP-103 STP-131 STP-370 SRP-370 SRP-372 SRP-372 SRP-372 SRP-500 Port : LPT	/ 256 Ial : 0 / 256 KByte #ation	Bitmap Selection Open File Remove Reset Download. Save File	Change Color Range THRESHOLD 0 R Value 100 L Value 100	Color R Color(Cattridge) L Color(Cattridge) Color Cha (Invert to)	C Red C Green C Blue C Not Use nge Select L Cartridge)

Send NV images to SRP350 1/4 6. Click Port Setting. After changing, Click "OK"

<i>,</i>	langing, or	ICK OF	•		
E	ommunication S	etting			×
	-Interface Setting				
	О СОМ	LPT	O US	В	
	Port	LPT1		•	
	BaudRate	9600		-	
	BitLength	8		7	
	Parity	NONE		7	
	StopBit	1		7	
	HandShake	DTR/D	SR	v	
		_			
	<u>0</u> K		E <u>x</u> it		

7. From Bitmap Selection, click "Open File"

NV Download Utility 3.7				×
No. Name	Size			
Logo Files : 0 / 256 Logo Size Total : 0 / 256 KByte	Bitmap Selection	Change Color Range	Color	C Red
Port Configuration	Upen File		R Color(Cartridge)	C Green
SRP-350	Hemove			C Blue
SAMSUNG SRP-370		R Value 100	L Color(Cartridge)	Not Used
Direct Port Configuration Port Setting	Download		Color Char (Invert to I	nge Select _ Cartridge)
Port : LPT1	Save File	L Value 100		
	Print		EXII	

8. Select Logo image file. Then click "Open".

Open		<u>?</u> ×
Look jn: [SamNV37 💽 🖛 🛍 📸	
NV Sample	512.BMP	
, File name:	NV Sample512 BMP	en
The <u>H</u> ame.		
Files of <u>type</u> :	Image Files(*.bmp)	cel

Send NV images to SRP350 2/4

9. Highlight the file, image preview will come out.

₩N¥ Download Utility 3.7			×
No. Name	Size	GR.	
1 NV Sample512.BMP			
Logo Files : 1 / 256 Logo Size Total : 13 / 256 KByte	Bitmap Selection	Change Color Range	- Color
Port Configuration SRP-350 SRP-350 Supercent Port	Remove		R Color(Cartridge) C Green
SAMSUNG SRP-370	Heset	R Value 100	L Color(Cartridge) Not Used Color Change Select (second the L Cartridge)
Port Setting Port : LPT1	Downloa Save File Print	d	

- 10. You can add more Logo images up to 256 images to the NV image memory, but it limited by images size.
- 11. After add all images you want to the list, Click "Download..."

NV NV Da	wnload Utility 3.7						×
No.	Name	Size					
1	NV Sample512.BMP	13	Anger a				
					-	, auta	
		- Diteres Calestin		- Change Calar D		Calar	
Logo Files Logo Size	:: 1 / 256 : Total : 13 / 256 KByte	Biuliap Selection		- change color ha	ange		O Red
- Port Cor	nfiguration	Open File		THRESHOLD	0	D. Calar(Carbidae)	C •
SRP-35	50 💽	Remove				h color(carringe)	U ureen
O Dire	ct Port C Windows Driver	Reset					C Blue
SAMSL	ING SRP-370 💌			R Value	100	L Color(Cartridge)	Not Used
Direct	Port Configuration					Color Char (Invertiou)	nge Select Cattridge 1
	Port Setting	Download				0111011101	- contrage (
Port : L	.PT1	Save File.		L Value	100		
		Print				EXIT	

12. Check the Printer, then click "Yes"



13. After Images loading finished, click "OK"



14. By checking the loaded NV image, click "Print"

<mark>NV</mark> N¥ Do	wnload Utility 3.7						×
No.	Name	Size	.				
1	NV Sample512.BMP	13					р
			and the second sec				
					A	, and a	
Logo Files	: 1 / 256 Total : 13 / 256 KBute	-Bitmap Selection-	,	Change Color Rai	nge	Color	C Red
- Port Con	fountion	Open File		THRESHOLD	0		- meu
SBP-35		Remove				R Color(Cartridge)	C Green
Direc	t Port C Windows Driver	Basat					C Blue
SAMSU	NG SRP-370			R Value	100	L Color(Cartridge)	Not Used
Direct	Port Configuration	Download	i			Color Cha (Invert to I	nge Select L Cartridge)
Port : L	PT1	Save File.		L Value	100	EXI.	r

15. Enter Selection = 1 and click "Print", NV image should print out.

Quality		Header	
Single <u>Hig</u>	hWide	None Header	
C Double W	ide		
O Double Hi	gh 	C Add Header	
O Double Hi	ghWide		
Printing Range			
O All	Sample) 1-2	3,4,5 7	
Selection	1		
		(<u>Print</u> E	<u>x</u> it
		E E	<u>x</u> it
		<u>Print</u> E	<u>x</u> it
		<u> </u>	<u>x</u> it
RitImage = 1		Erint E	<u>xit</u>
BitImage = 1		Erint E	<u>xit</u>
BitImage = 1		<u>Print</u> E	<u>x</u> it
BitImage = 1		Eint E	<u>xit</u>
BitImage = 1		Emini E	<u>sit</u>
BitImage = 1		<u>Pint</u> E	<u>sit</u>
SitImage = 1		Emit E	

Send NV images to SRP350 4/4