

Ref No.	Parts No.	Description	Remarks
1	E 62010670	Top case	Standard color
2	80-0159	OP sheet	
3	MD910	Printer MD910	
3	MD911	Printer MD911	24 columns 40 columns
4	E 4000-850	OP assy	
SW1,2	E 5102-430	SWITCH SKHHAN	
LED1,2	E 480-290	LED SEL2310E	
6	E 4000-970	PE Holder assy	
11	E 6611-405	Paper hook	
15	E 62020140	Bottom case	Standard color
16	E 6302-290	Foot	
18	E 4035-720	Schild plate	
19	E 4035-730	Ground sheet	
24	E 62040170	Printer cover (H) (ø 80 roll)	
25	E 62040180	Printer cover (ø 60 roll)	
34	76G23760	Screw M2 x 6	
35	76G22839	Screw M2.6 x 8	
37	76G40207	Screw M3 x 10	
	92ADU	AC adaptor 92AD-U	USA
	92ADJ	AC adaptor 92AD-J	JPN
	92ADE	AC adaptor 92AD-E	EUR

Ref No.		Parts No.	Description	Q'ty		Remarks
R	P			R	P	
		950037-00	PCB Assy 910-2 R JPN/EUR 24col	(1)		JPN/EUR 24col
		950038-00	PCB Assy 910-2 R USA 24col	(1)		USA 24col
		950039-00	PCB Assy 910-2 R JPN/EUR 40col	(1)		JPN/EUR 40col
		950042-00	PCB Assy 910-2 R USA 40col	(1)		USA 40col
		950040-00	PCB Assy 910-2 P 24 col		(1)	24 columns
		950041-00	PCB Assy 910-2 P 40col		(1)	40 columns
IC3	IC3	H130006-10	CPU M30620M8A	1	1	
IC4	IC4	H120012-00	EEPROM M24C02WMN6	1	1	
IC5	IC5	H150001-10	Reset IC M51953BPF	1	1	
IC2	IC2	H170007-10	Regulator M5237ML	1	1	
IC1	IC1	H170008-10	Regulator TA48M05F	1	1	
IC201		H160001-10	I/F IC SP232ECN	1	0	
	IC201,IC202	H110023-10	HCMOS SN74LV05APW	0	2	
	IC203	H110012-00	HCMOS 74LV74APW	0	1	
TA1-TA4,TA6	TA1-TA4,TA6	H240011-10	Transistor array FDS6912A	5	5	
TA5	TA5	H240012-10	Transistor array FDS8958A	1	1	
TR1	TR1	H200002-10	Transistor 2SA1720	1	1	
TR4,TR5,TR9	TR4,TR5,TR9	H220001-10	Transistor 2SC2712	3	3	
TR2,TR3	TR2,TR3	H290002-10	Transistor RN1302	2	2	
TR6,TR11	TR6,TR11	H290002-10	Transistor RN1302	2	2	
	TR202	H290002-10	Transistor RN1302	0	1	
	TR201	H280005-10	Transistor 2SK3018	0	1	
TR10	TR10	H280006-10	FET 2SJ327Z	1	1	
	TR201	H280005-10	FET 2SK3018	0	1	
XTAL1	XTAL1	H630008-10	Ceramic X'tal CSTCE10M0G52-R0	1	1	
SW2		H610001-10	DIPSW KSD08S	1	0	
	SW2	H610003-10	DIPSW KSD04S	0	1	
SW1	SW1	H650014-10	Power SW SK-22H03-G7	1	1	
CN1	CN1	H500050-10	Connector MOJ-D14	1	1	
CN2	CN2	H500051-10	Connector 5267-17A	1	1	
CN3		H500024-10	Connector 70013-025-03	1	0	
CN3		H500025-10	Connector 70013-025-04	1	0	
	CN3	H500027-10	Connector 57RE-40360-730B(D29)	0	1	
CN4	CN4	H500008-10	Connector 5267-06A	1	1	
F1	F1	H620012-10	Fuse SST2	1	1	
L1	L1	H640010-00	SC coil SC-03-05GS	1	1	
CN5	CN5	H500005-10	Connector 5267-03A	<1>	<1>	

7. Exploded View: CBM-910II

