
GST programming for SER-6500/6540/6500II/6540II



3. Description Program	
The character map refers user's manual page 124.	
 3.1. Logo Message Programming (Refer User's Manual page 72) A) Logo should include ABN number. B) Logo should include "TAX INVOICE" message. C) Set P-Mode Printing Option 15 as printing Logo. 5 0 SUB 1 5 X/TIME 1 SUB CASH 	
EXIT	
3.2. Display / Print Description Programming (Refer User's Manual page 71)A) Changing message "TAX AMT 1" to "GST AMOUNT"	
1 0 1 0 SUB 2 3 X/TIME	
G S T SP A M O U N T X/TIME CASH	
EXIT	
B) Changing message "TOTAL" to "TTL INC GST"	
1 0 1 0 SUB 4 X/TIME	
T T L SP I N C SP G S T X/TIME C	ASH
E	XIT
3.3. Financial Report Message Programming (Refer User's Manual page 71)A) Changing message "NONTAX" to "NON GST TTL"	
1 0 0 SUB 1 1 X/TIME	
N O N SP G S T SP T T L X/TIME C.	ASH
E	XIT

B) Changing message "TAX1 SALES" to "INC GST TTL"
1 0 0 SUB 1 2 X/TIME
I N C SP G S T SP T T L X/TIME CASH
EXIT
C) Changing message "TAX1" to "GST TOTAL"
1 0 0 SUB 1 6 X/TIME
G S T SP T O T A L X/TIME CASH
EXIT
3.4. Clerk Report Message Programming (Refer User's Manual page 72) A) Changing message "NONTAX" to "NON GST TTL" 1 0 3 0 SUB 2 X/TIME
N O N SP G S T SP T T L X/TIME CASH EXIT
B) Changing message "TAX1 SALES" to "INC GST TTL"
1 0 3 0 SUB 3 X/TIME
I N C SP G S T SP T T L X/TIME CASH
EXIT

C) Changing message "TAX1" to "GST TOTAL"

T

O

1 0 0 SUB 7 X/TIME ____

A

L

X/TIME

T

EXIT

4. Sample

G

S

Receipt

T

SP



Financial Report

CASH

ABC SHOP SHOP 1, SHOPPING CENTRE ABC TOWN		
ABN:74 123	456 789	
DATE 27/06/2 Z1 REPORT	2000 TUE 0005	
FINANCIAL		
NON GST TTL	-8.00	
INC GST TTL	•5.50	
GST TOTAL	*0.50	
NET SALE	3	
	=13.50	
GROSS SALES	*13.50	
CASH SALES	3	
	=13.50	
CASH-IN-D	*13.50	
DRMR 1	=13.50	
DRWR TTL	*13.50	
TAX INVOICE		
CLERK1	#01	
TIME 11:18	M0.000035	