

ECR 7900 MENU NAVIGATION CHART

MAIN MENU	
REGISTRATION MODE	>>
MANAGER MODE	>>
X1&2 REPORT MODE	>>
Z1&2 REPORT MODE	>>
PROGRAMMING MODE	>>
OFF MODE	>>

RESET PROCEDURE

The reset procedure must be carried out with the cash register switched off.

RESET FUNC.

PARTIAL RESET
SALES REPORT RESET
FULL RST W/O LANGUAGE
FULL RESET

NAVIGATION BASICS

Press **menu** to display the cash register's Main menu. Use **↑** and **↓** to navigate the menus and **TOTAL** to confirm a menu selection.

For a preset value field use **←** or **→** to view the values and **TOTAL** to set the value displayed.

For a free entry field, press **TOTAL** to enter Data Entry mode, type in the data and then press **TOTAL** again to save it. To return to the previous menu, or to switch from Data Entry mode to Navigation, mode press **ESC**.

To return to the Main menu, press **menu**. To switch off the menus, select **Off mode** from the Main menu.

If you press the wrong key at any time, an error is signaled with a beeping sound. Press **C** to clear the error condition and continue.

For all other details, see "Using the Menus" in the ECR 7900 User's Guide.

REGISTRATION MODE

CLERK LOGIN
TYPE THE CLERK NUMBER
TYPE THE CLERK PASSWORD

MANAGER MODE

PASSWORD ENTRY
ENTER THE
MANAGER PASSWORD
TYPE THE 4-DIGIT CODE
AND PRESS [ENTER]

X1&2 REPORT

FLASH REPORT
DEPT&FINANCIAL REPORT
DEPT RANGE REPORT >>
DEPARTMENT GRP REPORT >>
ALL PLUS REPORT
PLU RANGE REPORT >>
CLERK SALES REPORT
CLERK TRAINING REPORT
CLERK SALES/W TRAIN. >>
HOURLY REPORT
TRAINING REPORT
X2 DEPT&FINANCIAL REP.
EJ REPORT >>

Z1&2 REPORT

CHAIN REPORT >>
DEPT&FINANCIAL REPORT
DUPLICATE Z REPORT
ALL PLUS REPORT
CLERK SALES REPORT
CLERK TRAINING REPORT
CLERK SALES/W TRAIN. >>
HOURLY REPORT
TRAINING REPORT
Z2 DPT&FINANCIAL REP.
EJ REPORT >>

PROGRAMMING MODE

SALES PROGRAMMING >>
CONFIGURATION SETUP >>
PROGRAMMING DUMP >>
TRAINING MODE ON/OFF >>
SD MAINTENANCE >>
SYSTEM INITIALIZATION >>

EJ REPORT

FULL EJ REPORT
OLDEST EJ REPORT
LATEST EJ REPORT
DAILY EJ REPORT
EJ MEMORY CLEAR

EJ REPORT

FULL EJ REPORT
OLDEST EJ REPORT
LATEST EJ REPORT
DAILY EJ REPORT
EJ MEMORY CLEAR

SALES PRG

DEPARTMENT GROUP NAME >>
DEPARTMENT >>
PLU >>
%+/- SETUP >>
+/- SETUP >>
FOREIGN CURRENCIES >>
INSTORE BARCODE >>
HEADER MESSAGE >>
FOOTER MESSAGE >>
SCROLLING MESSAGE >>

PROGRAMMING DUMP

ALL DEPARTMENTS
DEPARTMENT RANGE >>
DEPARTMENT GROUPS >>
ALL PLUS
PLU RANGE >>
PLU LINK DEPARTMENT >>
OTHER SALES PROG
PRINT MODE
CLERK
ADVANCED SETTINGS
FREE CAPTION - 10 CHARS
FREE CAPTION - 24 CHARS
OTHER SETTINGS

CONFIGURATION SETUP

INITIAL SETUP
OPERATION MODE
RECEIPT PRINTING MODE
REPORT PRINTING MODE
CLERK SYSTEM
INDIVIDUAL CLERK
ELECTRONIC JOURNAL
FUNCTION KEY SETUP
ADVANCED SETTINGS
COUNTER SETTINGS
SHORT CAPTIONS
LONG CAPTIONS

TRAINING MODE ON/OFF

NOW ON, TURN OFF?
YES
NO

SD MAINTENACE

LOAD FROM SD-CARD
SAVE TO SD-CARD
FORMAT SD-CARD

SYSTEM INITIALIZATION

LANGUAGE : ENGLISH
PLU/EJ MEMORY : 2000/11000
SW DOWNLOAD : NO
ARE YOU SURE : NO

DEPARTMENT CODE ??#01

NAME : DEPT 01
DP GROUP LINK : 00
PRICE : 0.00
PRICE TYPE : NORMAL
SIGN : PLUS
TYPE : NORMAL
HALO : NOLMT
TAX STATUS : NOTAX
TAKE-OUT TAX : NOTAX

PLU CODE?#000000000001

NAME : PLU0001
DEPT LINK : 00
PRICE : 0.00
PRICE TYPE : OPEN
TAX STATUS : NOTAX
TAKE-OUT TAX : NOTAX

+/-SETUP

+ /-1 SIGN : MINUS
+/-1 HALO : NO LMT
+/-2 SIGN : MINUS
+/-2 HALO : NO LMT

%+/-SETUP

% 1 SIGN : MINUS
%1 RATE : 99.99
%1 RATE LIMIT : 0000
%2 SIGN : MINUS
%2 RATE : 00.00
%2 RATE LIMIT : 99.99

FOREIGN CURRENCIES #01

NAME : FC-1
DEC. POS. RATE : 0
DEC. POS. AMNT : 2
EXCH. RATE : 000001

INSTORE BARCODE #01

VERSION : LONG
FLAG CODE : 000
DIGITS IN FLAG : 0
DIGITS IN PRICE : 0
PRICE CK/DIGIT :NO
FC CONVERSION : NO FC
NEWSPAPER CODE :NO

SCROLLING MESSAGE

SCROLLING SPEED: MEDIUM
OFF MODE MESSAGE
PRG. Z.X. MODE MESSAGE >>
SALES MESSAGE >>
COURTESY MESSAGE 1 >>
COURTESY MESSAGE 2 >>

LOAD FROM SD-CARD

ALL PROGRAMMING DATA
PLU DATA
GRAPHIC LOGO

SAVE TO SD-CARD

ALL PROGRAMMING DATA
PLU DATA
GRAPHIC LOGO

FORMAT SD-CARD

ARE YOU SURE?
NO
YES

INITIAL SETUP

DATE FORMAT : DDMYY
DATE SETUP : 000000
TIME SYSTEM : 24H
TIME SETUP : 0000
ECR NUMBER : 000
KEY TONE : YES
RECEIPT MODE : RECEIPT
WINDING MOTOR : PS/XZ
EURO ROUNDING : NO
POWER SAVING : NO

OPERATION MODE

VAT CALC MODE : VAT
TAX1 RATE : 0.000
TAX2 RATE : 0.000
TAX3 RATE : 0.000
TAX4 RATE : 0.000
FC CONV TYPE : DIVIDE
%&+/- DEP CALC : NET
0 PRICE REG : YES
POSIT TENDER : YES
DECIMAL : 2
ROUNDING : OFF

RECEIPT PRINTING MODE

TAX RATE : YES
TOTAL TAX AMT : NO
TAX AMT/RATE : NO
TOTAL TAXABLE : NO
AMT/TAXABLE/RATE : NO
TX AMT W/O TAX : NO
T TAXL W/O TAX : NO
TAX SYMBOL : NO
TX DETAIL POS : AFTER
LINE SPACE : 1.00mm
PRINT FONT : NORMAL
GRAPHIC HEADER : NO
FOOTER : YES
HEADER : YES
DATE : YES
TIME : YES
CLERK NAME : YES
ECR NUMBER : YES
RECEIPT NUMBER : YES
PLU NUMBER : NO
SUBTOTAL : YES
MULTIPLE RCPT : YES

>>REPORT PRINTING MODE

X/Z FONT : COMP
EJ FONT : COMP
PRG FONT : COMP
Z1/Z2 COUNTER : YES
GT : YES
REFUND : YES
VOID : YES
%IN DEPT&PLU : NO
DUPLICATE Z : NO
ZERO SKIP RPT : YES
HEADER ON X/Z : NO

CLERK SYSTEM

CLERK SYSTEM : NO
PWD MANDATORY : NO
CLERK ENTRY : STAY
CLERK DISPLAY : YES

INDIVIDUAL CLERK #01

NAME : CLERK# 01
CLERK PWD : * * *
CLERK MODE : NORMAL
VOID ENABLE : YES
REFUND ENABLE : YES
(%) ENABLE : YES
(-) ENABLE : YES
PO ENABLE : YES
NEG DEPT ENABLE : YES

ELECTRONIC JOURNAL

EJ SYSTEM : DYNAMIC
EJ STORAGE : SALES
BEEP AT BEGINING : YES
BEEP AT END : YES

FUNCTION KEY SETUP

CASH >>
CHECK >>
CHARGE >>
CREDIT1 >>
CREDIT2 >>
CREDIT3 >>
CREDIT4 >>
CREDIT5 >>
CREDIT6 >>
PO/RA >>
#/NS >>

ADVANCED SETTINGS

FREE KEY LAYOUT >>
POPUP LIST FUNCTIONS >>
CHAIN FUNCTIONS >>
CHAIN REPORT >>
MANAGER PASSWORD >>

COUNTER SETTINGS

RECEIPT NUMBER : 0000
Z1 COUNTER : 0000
Z2 COUNTER : 0000
GT VALUE : 0.00
RECEIPT# RESET : NO
Z1&2 CT RESET : NO
GT RESET : NO

SHORT CAPTIONS

RESTORE DEFAULT :NO
02 COUPON
03 TL-COUPON
04 ADD-ON
05 TL-ADD ON
06 DISCOUNT
.....
60 FC

LONG CAPTIONS

RESTORE DEFAULT :NO
EJOURNAL USED
EJOURNAL FREE
REFUND.....
CLERK REPORT
.....
HOURLY REPORT

FREE KEY LAYOUT

01RESTORE DEFAULT : NO
02DEPT SHIFT&CODE 25
03DEPT KEY1 14
04DEPT KEY2 13
05DEPT KEY3 12
06DEPT KEY4 11
07DEPT KEY5 10
08DEPT KEY6 19
09DEPT KEY7 18
10DEPT KEY8 17
11DEPT KEY9 16
12DEPT KEY10 15
13DEPT KEY11 24
14DEPT KEY12 23
15DEPT KEY13 22
16DEPT KEY14 21
17DEPT KEY15 20
18DEPT KEY16 29
19DEPT KEY17 28
20DEPT KEY18 27
21DEPT KEY19 26
22#/NS(NEXT) IN PRG 04
23CLERK(ESC) 07
24RECEIPT ON/OFF 08
25SUBTOTAL 31
26CHECK 00
27CHARGE 00
28CREDIT1 00
29CREDIT2 00
30CREDIT3 00
31CREDIT4 00
32CREDIT5 00
33CREDIT6 00
34FC 00
35% 1 00
36% 2 00
37-/+ 1 00
38-/+ 2 00
39RA 00
40PO 00
41EC/VOID 00
42FULL VOID 00
43REFUND 00
44PLU CODE 06
45PLU ALT 03
46ADD PLU 00
47PLU INQUIRY 00
48HOLD RECALL 09
49PAY TRANSFER 32
50TAKE-OUT 00
51CHAIN FUNCTION 1 00
52CHAIN FUNCTION 2 00
53CHAIN FUNCTION 3 00
54CHAIN FUNCTION 4 00
55CHAIN FUNCTION 5 00
56POP LIST FUNCTION1 33
57POP LIST FUNCTION2 02
58POP LIST FUNCTION3 05
59POP LIST FUNCTION4 01
60POP LIST FUNCTION5 30

POPUP LIST #01

RESTORE DEFAULT : NO
RECEIPT ON/OFF : NO
SUBTOTAL : NO
CHECK : YES
CHARGE : YES
CREDIT1 : YES
CREDIT2 : YES
CREDIT3 : YES
CREDIT4 : YES
CREDIT5 : YES
CREDIT6 : YES
FC : NO
%1 : NO
%2 : NO
-/+1 : NO
-/+2 : NO
RA : NO
PO : NO
EC/VOID : NO
FULL VOID : NO
REFUND : NO
PLU CODE : NO
PLU ALT : NO
ADD PLU : NO
PLU INQUIRY : NO
HOLD RECALL : NO
PAYMT TRANSFER : NO
TAKE-OUT : NO

CHAIN FUNCTION #01

PRESS CHAIN FUNCTION KEYS THAT

CHAIN REPORT #01

DEPT&FINANCIAL : NO
DEPT GROUP : NO
ALL PLU : NO
SALES CLERK : NO
TRAINING CLERK : NO
HOURLY REPORT : NO
TRAINING : NO
DPT&FINIAL GT : NO
FULL EJ : NO

MANAGER PASSWORD

PRG&Z MODES : 0000
X MODE : 0000
MANAGER MODE : 0000
TRAINING MODE : 0000

CASH

NAME : CASH
HALO : NO LMT
TNDR MANDATORY : NO
CHANGE ALLOWED : YES
DRAWER OPEN : YES

PO/RA

PO HALO : NO LMT
PO HEADER PRNT : YES
RA HALO : NO LMT
RA HEADER PRNT : YES

#/NS

DRAWER OPEN : YES
MODE ALLOWED :REG/MGR
RECEIPT PRINT : YES
HEADER PRINT : YES
SAVE IN EJ : YES
UPDATE RECPT# : YES